







## FEATURES

1. Tally Counter counts from 0 to 9999.
  - Switch between + or – mode to add or subtract the count.
2. Largest digital display.
3. Easiest to use.
4. : Power on/off button.
5. Sleep mode after 2 hours of inactivity to save battery power.
6. : Beep confirmation sound is on when the symbol shows.
7. : Lock feature prevents accidental modification.

## HOW TO OPERATE

1. Remove battery insulation film first.
2. Press + button to enter + mode and – button to enter – mode. (+/- will show on the display)
3. In + mode, press  button to add the counter by 1.
4. In – mode, press  button to subtract the counter by 1.




## TO RESET TO ZERO

1. Press RESET button and a STOP sign will show on the display.
2. Press  button to count again and cancel reset.
3. Press RESET button again to reset the count to 0.


## POWER ON/OFF

1. Hold RESET button 3 seconds to power OFF the display.
2. The display will blank when no activity has been detected for 2 hours.
3. Press any button to power ON the unit.

## 

1. Hold  button 3 seconds to turn the beep sounds on/off. ( symbol appears/disappears)
2. Hold both  & RESET button 3 seconds to turn the lock feature on/off.

( symbol appears/disappears)

**Note: when the  symbol shows, every button will be locked. You will need to unlock the device before starting to use it again.**

## BATTERY REPLACEMENT

1. Remove the battery cover on the back side of the body with a coin or similar tool, using the arrows as direction indicators.
2. Remove and replace the battery with type LR44 or equivalent.
3. Be sure that " + " side is up.
4. Replace the battery cover and lock into place.